

Qlamp LED ceiling light with emergency function 16W

Q-CL3027



DESCRIPTION:

This lighting is auto-managed by AC direct power or battery backup, that is, when power failure, the battery backup will be responsible for the power supply of 1 watt. The battery backup can continuously supply power for more than 3 hours or even more. It is widely applied in the corridor, washing room, elevator lobby etc. In most cases, it is necessary and wise to choose the emergency light, for that occasional power outage will cause trouble, or even danger.

EMERGENCY FUNCTION

1. The unit will charge automatically (LED is green). A single LED remains on when the supply is interrupted.
2. Verify that the Green LED is illuminated; this confirms that the batteries are charging.
3. Charge the battery for at least 24 hours before first use.
4. If the LED is not illuminated then there may be no a.c supply, the battery has not be connected properly or the internal circuit may have failed.
5. The battery should be re-charged and checked every three months.
6. The battery should be discharged and the duration of the lamp in emergency mode checked every six months.

TECHNICAL SPECIFICATION

Model No.	Q-CL3027
Size	280*280*87mm
Power	16W Max.(AC) 1W Max.(DC)
Input Voltage	100-130V/AC, 220-240V/AC 50/60Hz
CCT	2700-6400K
Lumens Output	940lm
LED type	SMD5630, 36pcs
Housing Material	ABS body and PC diffuser
Battery	Emergency set, lithium battery, 1300mA, 3.7V
Continuous illumination time	3 hours (180 minutes)
Color	Opal cover + white base Transparent cover + white base
IP Rating	IP65



POWERSAVE SOLUTIONS LTD

HEAD OFFICE: Unit 7, The Sandon Estate, Sandon Way, Liverpool L5, 9YN

LONDON OFFICE: 152-154 Coles Green Road, NW2 7HD

e-mail: info@powersavesolutions.co.uk facebook.com/powersavesolutions www.powersavesolutions.co.uk